

*Parameters Subject to Change Without Notice*

## DESCRIPTION

The JW<sup>®</sup>5079C is a monolithic buck switching regulator based on I2 architecture for fast transient response. Operating with an input range of 5.5V~23V, JW5079C delivers 10A of continuous output current with two integrated N-Channel MOSFETs. The internal synchronous power switches provide high efficiency without the use of an external Schottky diode. At light loads, the regulator operates in low frequency to maintain high efficiency and low output ripples. JW5079C guarantees robustness with output short protection, thermal protection, current run-away protection, and input under voltage lockout.

JW5079C is available in QFN3×3-20 package, which provide a compact solution with minimal external components.

Company's Logo is Protected, "JW" and "JOULWATT" are Registered Trademarks of JoulWatt technology Inc.

## FEATURES

- 5.5V to 23V operating input range
- 10A output current
- Up to 95% efficiency
- High efficiency at light load
- 600kHz frequency
- Fixed 5V LDO output supplies 200mA
- Input under voltage lockout
- Power good indicator
- Output discharge function
- Output Over/Under Voltage Protection
- Output short protection
- Thermal protection
- Available in QFN3X3-20 package

## APPLICATIONS

- Industrial and commercial low power system
- Computer peripherals
- LDO monitors and TVs
- Green Electronics/ Appliances

## TYPICAL APPLICATION

